

SSA3000X Firmware Update Instructions

Note: During the updating, do not cut off the power or pull out the U-disk and if the upgrade process gets stuck, please contact SIGLENT immediately at support@siglent.com.

1. Please firstly unzip the firmware file (.ADS) in the update package to a U-disk.
2. Insert the U-disk.
3. Press **System** and then press **System Info**, we can enter **Firmware Update** in sys info menu.




Figure 1 System Info function menu

4. Press **Firmware Update** and then enter the file system (or you can press **File** button to enter the file system).




Figure 2 File system

5. Use the universal knob to select the right update firmware which should be with an ADS postfix. Press **Open/Load**, we will see an info window then and then press **Enter** to run upgrade program. It will take about 1~2 minutes.




Figure 3 Update

6. After the spectrum analyzer restarted, we can check the version information in sys info.

Note: During the updating, do not cut off the power or pull out the U-disk and if the upgrade process gets stuck, please contact SIGLENT immediately at support@siglent.com.